

## MK7C & MK10A WC/CT DISPLAY SEQUENCE

### MK7C

#### Set A Scrolling Display

| Set | LCD Desc | Display | Unit | Displayed   | Description  |
|-----|----------|---------|------|-------------|--|
| A   | TIME     | tInE    |      | HH:MM:SS    | Current Time (DLS Applied)                             |
| A   | DATE     | dAtE    |      | DD.MM.YY    | Current Date ( DLS Applied)                            |
| A   | R1       | r1      | KWh  | 00000000    | Accum, CH1: Import wh Total, Cumulative Total, Rate A  |
| A   | R2       | r2      | KWh  | 00000000    | Accum, CH1: Import wh Total, Cumulative Total, Rate B  |
| A   | TO       | to      | KWh  | 00000000    | Accum, CH1: Import wh Total, Cumulative Total, Unified |
| A   | WPD      | uPd     |      | 08457448900 | Vendor Phone Number                                    |

#### Set B displayed by holding down SELECT Button on MK7C

|   |      |      |      |          |   |
|---|------|------|------|----------|---|
| B | MDIW | ndlu | KW   | 0.00     | Max D, CH1: Import wh Total, Current, Unified           |
| B | MDIV | ndlu | KVA  | 0.00     | Max D, CH5: Import VAh Total, Current, Unified          |
| B | MDIT | ndlt |      | HH:MM:SS | Max DT, CH1: Import wh Total, Current, Unified          |
|   |      |      |      | DD.MM.YY |   |
| B | MDIC | ndIC |      | 1        | Billing Reset Count                                     |
| B | EW   | Eu   | KWh  | 0        | Accum, CH2: Export wh Total, Cumulative Total, Unified  |
| B | EVA  | EuA  | KVAh | 0        | Accum, CH6: Export VAh Total, Cumulative Total, Unified |
| B | GSM  | GSn  |      | 99       | Modem Signal Strength                                   |
| B | VL1  | uL1  | V    | 000.000  | Voltage   |
| B | IL1  | IL1  | A    | 0.000    | Main Current  |
| B | POW  | Pou  | KW   | 0.0000   | Active Power (Total)                                    |
| B | PF   | PF   |      | 1.000    | Power Factor  |
| B | FREQ | FrEq |      | 00.000   | Frequency   |
| B | SSC  | SSC  |      | SSC_0000 | Miscellaneous String                                    |

### MK10A WC/CT

#### Set A Scrolling Display

| Set | LCD Desc | Display | Unit | Displayed   | Description  |
|-----|----------|---------|------|-------------|--|
| A   | TIME     | tInE    |      | HH:MM:SS    | Current Time (DLS Applied)                             |
| A   | DATE     | dAtE    |      | DD.MM.YY    | Current Date ( DLS Applied)                            |
| A   | R1       | r1      | KWh  | 00000000    | Accum, CH1: Import wh Total, Cumulative Total, Rate A  |
| A   | R2       | r2      | KWh  | 00000000    | Accum, CH1: Import wh Total, Cumulative Total, Rate B  |
| A   | TO       | to      | KWh  | 00000000    | Accum, CH1: Import wh Total, Cumulative Total, Unified |
| A   | WPD      | uPd     |      | 08457448900 | Vendor Phone Number                                    |

#### Set B displayed by holding down SELECT Button on MK10a

|   |       |       |       |          |  |
|---|-------|-------|-------|----------|--|
| B | IVAR  | IuAr  | KVArh | 0        | Accum, CH3: Import varh Cumulative Total, Unified        |
| B | IVA   | IuA   | KVAh  | 0        | Accum, CH5: Import VAh Cumulative Total, Unified         |
| B | MDIW  | ndlu  | KW    | 0.00     | Max D, CH1: Import wh Total, Current, Unified            |
| B | MDIVA | ndluA | KVA   | 0.00     | Max D, CH5: Import VAh Total, Current, Unified           |
| B | MDIT  | ndlt  |       | HH:MM:SS | Max DT, CH1: Import wh Total, Current, Unified           |
|   |       |       |       | DD.MM.YY |  |
| B | MDIC  | ndIC  |       | 0        | Billing Reset Count                                      |
| B | EW    | Eu    | KWh   | 0        | Accum, CH2: Export wh Total, Cumulative Total, Unified   |
| B | EVAR  | EuAr  | KVArh | 0        | Accum, CH4: Export varh Total, Cumulative Total, Unified |
| B | EVA   | EuA   | KVAh  | 0        | Accum, CH6: Export VAh Total, Cumulative Total, Unified  |
| B | GSM   | GSn   |       | 99       | Modem Signal Strength                                    |
| B | VL1   | uL1   | V     | 000.000  | Phase A Voltage  |
| B | VL2   | UI2   | V     | 000.000  | Phase B Voltage  |
| B | VL3   | uL3   | V     | 000.000  | Phase C Voltage  |
| B | IL1   | IL1   | A     | 0.000    | Phase A Current  |
| B | IL2   | IL2   | A     | 0.000    | Phase B Current  |
| B | IL3   | IL3   | A     | 0.000    | Phase C Current  |
| B | POW   | Pou   | KW    | 0.0000   | Active Power (Total)                                     |
| B | CT    | Ct    |       | 1        | Primary Current Ratio                                    |
| B | PF    | PF    |       | 1.000    | Power Factor   |
| B | FREQ  | FrEq  |       | 00.000   | Frequency  |
| B | SSC   | SSC   |       | SSC_0000 | Miscellaneous String                                     |